

HEX04 & HEX05 Instruction Manual

PERFORM
FX



RGBAWUV LED Par Light



CAUTION - ATTENTION - VORSICHT

**RISK OF ELECTRIC SHOCK- DO NOT OPEN
RISQUE D'ELECTROCUTION- NE PAS OUVRIR
STROMSCHLAGEFAHR- NICHT OFFNEN**



**In Compliance with the following directives: RoHS Directive
(2002/95/EU) and WEEE Directive (2002/96/EU)
If this product is no longer functional or reaches the end of its
usable life, please take it to an approved recycling plant.**

CE



Version 1.0

www.terralec.co.uk

Dear Customer,

Thank you for purchasing the Perform FX HEX04/05 LED Fresnel. With decades of experience in design and production, Perform FX is one of the leading manufacturers of Professional Lighting and Effects equipment. This unit has been designed and manufactured to the highest standards so you can be assured you have made a good investment.

For your safety and to ensure you make full use of the HEX04/05 features, please make sure you read this manual in full.

Before Use

- Before you start using this unit, please check to ensure there's no transportation damage. Should there be any, do not use the device and consult with your dealer first.
- **Important: This device left our factory in perfect condition and well packaged. It is absolutely necessary for the user to strictly follow the safety instructions and warnings in this user manual. Any damage caused by mishandling is not subject to warranty. The dealer will not accept responsibility for any resulting defects or problems caused by disregarding this user manual.**
- Keep this booklet in a safe place for future consultation. If you sell the unit, be sure to add this user manual.
- To protect the environment, please try to recycle the packing material as much as possible.

Safety Instructions:

- Read this manual in full before operating this product.
- Keep this manual in a safe place for future reference.
- Heed all warnings and instructions, both in this manual and on the product.
- Carry and transport this product with care. Dropping this product may result in serious mechanical failure.
- The manufacturer accepts no responsibility for injury or damage caused as a result of not following the manual provided.
- Turn off and unplug this light from mains supply when not in use.
- This light is not waterproof and should not be used outside.
- Do **NOT** modify this product in any way.
- In the event of any liquid entering the housing, unplug immediately & contact a qualified engineer.

Protection from Fire:

- Do not place near sources of heat or ignition.
- Do not cover or block any ventilation holes.
- Check your AC wall socket will take the power you are applying to avoid overloading the mains supply.

Protection from Electric Shock:

- Only connect this unit to a mains socket with suitable trip and RCD protection.
- To disconnect from the mains socket, always remove by the mains plug. Do not attempt to remove by pulling the mains cable.
- Disconnect the unit from the mains supply before cleaning. Cleaning should be carried out with a soft, dry cloth.
- Do not expose this unit to any liquids.
- To prevent damage to the product or electric shock, do not expose or operate this device or its power supply to rain or moisture.
- Choose a suitable route for mains cables, ensuring trip hazards are avoided and the mains cable is not at risk of being crushed.
- Do not open this unit to service. There are no user serviceable parts inside. Any servicing or repairs should be carried out by a qualified engineer only. **Any attempt to service or adapt this unit will leave your warranty void** and could result in serious malfunction or injury.

Protection from Injury and Damage:

- Do not attempt to modify this unit.
- Always install the unit in a suitable location where vibrations to the unit are avoided.
- Check this unit matches the mains voltage and frequency before plugging it in to your mains socket.
- In the event that any object or liquid enters the machine, switch off immediately, remove from mains and consult a qualified engineer.
- Should you experience any malfunction or damage to the mains cable, disconnect from the mains supply immediately and consult a qualified engineer.
- All parts should be replaced with genuine spare parts and carried out by a qualified engineer.

Overhead Rigging:

- The installation must be carried out by a qualified engineer only. Improper installation can result in injuries or damage to property.
- Overhead rigging requires experience. Working loads should be adhered to, certified materials should be used.
- The installed device should be regularly inspected for safety.
- Make sure the working area is clear from people and obstructions during rigging, derigging and servicing.
- Locate the light in a well-ventilated area away from flammable materials and liquids.
- When mounting make sure the installation point can take the weight.
- Make sure a safety chain or wire is always used and can take the weight of the light.
- The light should be well fixed and free from swinging.
- Do not cover any ventilation holes.
- The light must not be powered when it is not to be used for an event.
- The operator must make sure the light fitting has been installed correctly to all the necessary guidelines before each use.
- **The installation should be inspected every 6 months.**

Product Information:

Contents and Unpacking:

Before beginning your initial setup, check the unit has not been damaged in transit. In the event there is damage to the housing, cable or internal components, contact your dealer immediately.

Contents:

- 1 x RGBAWUV PAR Light
- 1x Mains Lead
- 1x User Manual
- 1x Barn Door

Product Description:

An extremely powerful LED Par Can housed in a tough metal case complete with barn doors. The eighteen 12-watt HEX LEDs should provide enough output for even the most demanding applications; giving the user almost unlimited colour options; with red, green, blue, amber, white and UV LEDs all included. With smooth colour mixing, virtually no heat output and only 150 watts power consumption, this light is suitable for many applications from theatres to clubs and bars.

Users can enjoy a variety of control options. For DMX, there are 6 or 11 channels, giving control over each colour and the lights built-in programmes. For ease of wiring these units have daisy chaining available for both the DMX signal (3 pin sockets) and power supply (Powercon). Furthermore, the dual bracket allows for floor standing or elevated hanging. Available in 25- or 40-Degree beam angle options. The temperature-controlled fan will ensure quiet operation when not in use.

Product Specification:

Power Supply: 100-240 Vac 50/60Hz

Power Consumption: 150 Watts

LED: 18 x 12 watt RGBAWUV

Beam Angle: 25 or 40 Degrees

DMX Channels: 6, 11

Dimensions: 330 x 300 x 250mm (Barn door closed)

Weight: 4.45kg

Product Information:



	Name	Use
1	Barn door	Barn door facilitates shaping of the beam of light from the fixture. Prevents light spill into areas where they are not wanted.
2	Display and Menu Buttons	Used to adjust the units settings.
3	Hanging Bracket	You can use the hole in the centre of the bracket to fix a hanging clamp.

Product Information:



	Name	Use
4	Menu Button	Used to enter the setup menu.
5	Up Button	Used to go to the previous menu or increase parameter value.
6	Down Button	Used to go to the next menu or decrease parameter value.
7	Enter Button	Used to select a menu option or confirm a setting.
8	Display	Shows the various menus and selected functions.
9	Main Input	Equipped with professional Locking Connectors. Connect with the supplied cable or any suitable Neutrik PowerCon.
10	Mains Output	Used to daisy chain the power of several other projectors. Always pay attention to the maximum load.
11	Mains Fuse	Protects the unit in case of electrical problems. Always use the same fuse.
12	DMX Output	3 pin XLR output to daisy chain to other DMX lights.
13	DMX Input	3 pin XLR input to allow connection from other DMX lights or DMX Controller.

Menu Layout:

MENU	Submenu	Function
Addr	A001-A512	DMX Address
xxCh	6Ch/ 11Ch	DMX Channels
StAT	r 000- r255	Red Dimmer
	G 000- G255	Green Dimmer
	b 000- b255	Blue Dimmer
	U 000- U255	White Dimmer
	a 000- a255	Amber Dimmer
	P000-P255	Purple Dimmer
run	SU0-99	Sound Sensitivity
	Pu0-99	Pulse with speed adjust
	FA0-99	Fade change with speed adjust
	Ch0-99	Jump change with speed adjust
Lock	YES	Delayed 10s Lock screen
	NO	Does not Lock screen
SIGN	OFF	No Function
	NO	No Function
MODE	SLAV	Slave Mode
	MAST	Master Mode
	ALON	Alone Mode
t	XX	temperature

Setting a DMX address:

To set a DMX address, press "MENU" until the display shows "Addr".
Press "ENTER". Use the "Up" and "Down" buttons to set the desired address.
Press "ENTER" to save.

DMX Channel Mode:

There are two DMX channel layouts- 6 or 11.
To set the desired channel layout, press "MENU" until the display shows "XXCH".
Press "ENTER" and adjust using the "Up" and "Down" buttons.
Then press "ENTER" to save.

Static Colours:

To set a desired Static Colour, press "MENU" until the display shows "STAT" on LED Display. Press "ENTER".
To adjust a colour, use the "Up" and "Down" buttons to select the desired colour.
Press "ENTER" and use the "Up" and "Down" buttons to adjust the colour's brightness, then press "ENTER".
Repeat until the desired colour is produced.

Run Built in Programme:

To run a built in programme, press "MENU" until "RUN" is displayed.
Press "ENTER" and use the "Up" and "Down" buttons until "SU/PU/FA/CH".
Press "ENTER" on the desired programme and use the "Up" and "Down" buttons to adjust the speed/ sound sensitivity.

Lock:

Lock function stops the menus setting being tampered with. If "YES" is selected, the settings cannot be changed without entering a code: "Up, Down, Up, Down".

Mode:

Used to set stand alone, master or slave.

Master Slave Mode:

Up to 16 fixtures can be used Master Slave. In Master Slave mode, the first light needs to be set to the master and the rest of the lights need to be set to slave. The first light (master) controls the other lights. DMX cables need to be connected from the master light to the rest of the slave lights. The master light can be used with its built programmes, or a static colour can be selected.

Notes:

After 10 seconds the display will turn off. Press any button to turn the display back on.
After setting parameters, parameters will be saved after a few seconds.
When a DMX signal is detected, the DMX signal will override all built in programmes.

DMX Layout:

11 Channels Mode:

11 Channel	Function	Description
CH1	Master Dimming	R/G/B/W/A/UV Dimming, Linear dimming
CH2	Red Dimming	R Dimming, Linear dimming, From dark to light
CH3	Green Dimming	G Dimming, Linear dimming, From dark to light
CH4	Blue Dimming	B Dimming, Linear dimming, From dark to light
CH5	White Dimming	W Dimming, Linear dimming, From dark to light
CH6	Amber Dimming	A Dimming, Linear dimming, From dark to light
CH7	Purple Dimming	UV Dimming, Linear dimming, From dark to light
CH8	Strobe	R/G/B/W/A/UV Strobe from slow to fast
CH9	Shut down	0-5: DimmerCurve Linear
		6-10: DimmerCurve Exponential_curve
		11-15: DimmerCurve Logarithmic_curve
		15-20: DimmerCurve S_Curve
		21-255: fast shut down
CH10	Function Selection	0-50: No Function
		51-100: Jump change
		101-150: Gradual change
		151-200: Pulse variable
		201-255: Sound activated
CH11	Function Speed	Function speed, from slow to fast

6 Channels Mode:

11 Channel	Function	Description
CH1	Red Dimming	R Dimming, Linear dimming, From dark to light
CH2	Green Dimming	G Dimming, Linear dimming, From dark to light
CH3	Blue Dimming	B Dimming, Linear dimming, From dark to light
CH4	White Dimming	W Dimming, Linear dimming, From dark to light
CH5	Amber Dimming	A Dimming, Linear dimming, From dark to light
CH6	Purple Dimming	UV Dimming, Linear dimming, From dark to light

DMX Basics:

DMX is short for “digital multiplexer”, which is a universal protocol designed for the entertainment industry. It allows control of intelligent fixtures like scanners, moving heads, LED par cans, dimmer packs and effects machines etc. DMX allows you to control many fixture channels, normally up to 512, with varying channels from 0-255 (0-100%). This will give control of channels such as gobo selection, movement, colours, dimming and timing to name just a few.

DMX is a very good system, as all this information can be sent down one cable. Used in conjunction with a DMX controller with memory, all your channel settings can be saved and recalled easily.

DMX was designed so that all manufacturers can use the same protocol/ language to control their fixtures, allowing the end user to use any make fixture from their DMX controller, as long as both are DMX compatible, and the controller has enough channels to control the fixture that is attached. Fixtures have an input and output DMX socket, allowing you to connect from the controller to the first fixture then from that fixture to the next (this is often referred to as ‘daisy chaining’). Sockets are normally 3 pin XLR but can be 5 pin XLR.

DMX fixtures need to have a DMX address set, this is so they can then decode the correct information from the controller. This is normally done by a digital display panel, where the address can be changed by simple up and down buttons; the system address ranges from 1-512. Alternatively, it may be controlled by a row of small switches, called dip switches; on this type of system, the required address is then converted to a binary number.

To work out your dip switch settings you can simply download a DMX calculator from the internet. The order in which fixtures are connected in a DMX line does not influence the DMX address, a fixture set to DMX address 1 can be put in a DMX line anywhere from beginning, middle to end. As long as it has its address set to 1, it knows to take information from that point onward.

3 Pin	5 Pin
Pin 1 GND	Pin 1 GND
Pin 2 -	Pin 2 -
Pin 3 +	Pin 3 +
	Not Used
	Not Used

DMX Wiring and Connections:

3 pin DMX wiring is more common, although using a 5 pin connector is better to stop confusion with audio leads. With 5 pin connections, not all pins are used, though it is worth checking your manual for your fixture, as some lights use the unused pins for low voltage control.

To avoid erratic behaviour from your fixture, ensure when making cables, you always use suitable DMX cables and do not connect pin 1 GND to the outer casing of the connector (as you may do with your audio cables). Do not make “Y” leads to split cable fixtures; always use the in and out sockets or a DMX splitter.

We also recommend you put a DMX terminator in any fixture which does not have a DMX lead connected from the output socket to another fixture; to reduce unexpected behaviour. A DMX terminator is simply a male XLR plug with 120 Ohms, ¼ watt resistor, soldered across pins 2 and 3. You can also buy these pre-made.


Example of a DMX Fixture with 5 Channels:

Ch1	Ch2	Ch3	Ch4	Colour	
Pan	Tilt	Shutter/Shaking	Gobo	Normal	Split
540°	270°	246-255 Open	255 Fastest speed Gobo change	255 Fastest speed Rainbow Effect	255 Fastest speed Rainbow Effect
		247 Fastest speed shaking			
			120-127	128 Slowest speed Rainbow effect	128 Slowest speed Rainbow effect
		132 Slowest speed shaking	111-119	118-127 Pink	121-127 Pink
			103-110	107-117 Yellow	113-120 Yellow+Pink
		131 Fastest speed shutter	094-102	096-106 Orange	106-112 Yellow
			086-083	086-095 Light Green	098-105 Orange+Yellow
		16 Slowest speed shutter	077-085	075-085 UV Purple	083-090 Light Green+Orange
			069-076	064-074 Blue	076-082 Light Green
		008-015 Open	060-068	054-063 Red	068-075 UV Purple
			052-059	043-053 Amber	061-067 Blue
		000-007 Blackout	044-051	032-042 Light Blue	053-060 Red+Blue
0°	0°		035-043	022-031 Magenta	046-052 Red
			0-26-034	011-021 Green	038-045 Amber
			018-025	000-010 White	031-037 Light Blue
			009-017		023-030 Magenta
			000-008		016-022 Green+Magenta
					008-016 Green
					000-007 White

Each fixture takes up to 5 DMX Channels (see above):

You have a cable from the controller to the first fixture cable, then from first to second and so on. The last light then has a DMX terminator plugged in.

Example of a DMX Line



Fixture 1 would be set to DMX address:
DMX Address 1
 Fixture 2 would be set to DMX address:
DMX Address 6
 Fixture 3 would be set to DMX address:
DMX Address 11
 Fixture 4 would be set to DMX address:
DMX Address 16

We recommend you to read manuals for your DMX fixture and controller in full. Some controllers tell you what each fixture address needs to be, and some lights need other settings changed before they will work.

When setting your DMX address, you must ensure fixtures don't overlap from one to the next. You can set two fixtures to the same address, and as long as they are the same fixture (i.e. same channel layout) then they will do the same as each other.

**Thank you for taking the time to read this information.
For further information, please contact sales@terralec.com or visit
www.terralec.co.uk**