



L345B
12V 20W LED FLOODLIGHT

IMPORTANT

Installer and Users please note:

These instructions should be read carefully and left with the user of the product for future reference.

BEFORE USE

You must inspect the luminaire including its cable for any signs of damage. If the product is damaged, DO NOT use it, and contact your supplier immediately.

INSTALLATION

Remove the fixing bracket from the body of the luminaire.

Attach the fixing bracket to a wall or post, using screws and, if necessary, wall plugs.

Fit the body of the luminaire into the fixing bracket.

Connect the luminaire to the 12V dc supply using the cable provided.

- Red = + Positive
- Black = - Negative (Ground)

If mounting outdoors then make sure that the connections are adequately waterproofed.

GENERAL SAFETY REQUIREMENTS

- All electrical work must be carried out to the requirements of the latest edition of the IEE wiring regulations (BS7671).
- Domestic wiring must be tested periodically by a qualified electrician at least once every 10 years or at every change of occupancy.

DISPOSAL AND RECYCLING

You must not dispose of this luminaire with domestic household waste.

Most local authorities have specific collection system for appliances and disposal is free of charge to the end-user.

When replacing an existing luminaire with a similar new luminaire your retailer may take the old luminaire for disposal.

TECHNICAL SPECIFICATION

Spec	L345B
Dimension (mm)	95x110x80
Weight (Kg)	0.45
LED Power (W)	20
System Power (W)	22
Light Output (Lumens)	1600
Lumen Efficacy	80
Colour Temperature	5000
IP Rating	IP65
Power Factor	>0.8
ERP Energy Rating	A
Viewing Angle	120°
Ambient Temperature	-10° to +40° C

SERVICE WARRANTY

- Electrovision guarantees the product free from defects in materials and workmanship for a period of 2 Years.
- Should this appliance be operated under conditions other than those recommended, at voltages other than the voltage indicated on the appliance, or any attempts made to service or modify the appliance, then the warranty will be rendered void.
- The product you buy may sometimes differ slightly from illustrations. This warranty is in addition to, and does not affect, your statutory rights.
- Our guarantee is administered by our retailers.
- If your product arrives damaged, you must contact the retailer from whom you bought it. The retailer's contact details will be on the invoice that arrived with the product, or on the e-mail you received when you placed the order. Do not contact Electrovision, only your retailer can arrange a replacement.
- If your product fails within the guarantee period, and needs to be repaired or replaced, you must contact the retailer from whom you bought it.
- The retailer's contact details will be on the invoice that arrived with the product, or on the e-mail you received when you placed the order.
- If you have just received your product and require technical help in using it, please call our Help Desk on (0845) 459 4816
- If you have any other technical queries about the product, please call our Help Desk on (0845) 459 4816.

Electrovision Ltd.,
Lancots Lane, Sutton,
St. Helens, Merseyside.
WA9 3EX

website: www.electrovision.co.uk